

NO	Type	Voltage	Volume (Ah)			Dimensions (mm)				Weight (kg)	Container	Description
			C1	C3	C10	Length L	Width W	Height H	Total Height H			
1	12 SB 6.5 (Motorcycle)	12	2.57	4.87	6.5	151	65	94	98	2.7	ABS	كابل مبدل سوکت به پوچ و مبره (العدد) (Motorcycle)
2	6 SB 4.5	6	2.34	3.18	4.5	70	47	100	105	0.9	ABS	
3	12 SB 4.5	12	2.34	3.18	4.5	89.3	69.3	101	106.2	1.8	ABS	
4	12 SB 7.5	12	3.9	5.3	7.5	151	65	94	98	2.7	ABS	
5	12 SB 9	12	4.68	6.36	9	151	65	94	98	2.85	ABS	
6	12 SB 9 (Motorcycle)	12	4.68	6.36	9	136.4	76.5	134.3	134.3	2.9	ABS	(Motorcycle)
7	12 SB 12	12	6.2	8.5	12	151	98	95	100	3.8	ABS	
8	12 SB 18	12	9.4	12.9	18	181	78	165	165	5.8	ABS	
9	12 EV 20	12	13.1	17.7	20	181	77	170	170	7.3	ABS	
10	12 SB 28	12	14.5	19.8	28	175	166	125	125	9	ABS	
11	12 SB 42	12	22	30	42	197	166	169	169	13.1	ABS	
12	12 SB 65	12	34	46.5	65	349	167	180	185	23.85	ABS	
13	12 SB 100	12	55	75	100	328	172	216	222	32	ABS	
14	12 SB 100 (Deep Cycle)	12	55	75	100	328	172	216	222	30.5	ABS	
15	12 SB 100 (FT)	12	55	75	100	394	110	285	285	33	ABS	(Front Access)
16	12 SB 150 (FT)	12	82	112	150	551	110	288	288	47	ABS	(Front Access)
17	12 SB 155 (W:110)	12	84	114	155	551	110	288	288	49	ABS	(Front Access)
18	12 SB 155 (FT)	12	84	114	155	560	126	280	280	54	ABS	(Front Access)
19	12 SB 200 (FT)	12	106.1	142.5	200	560	126	320	320	64	ABS	(Front Access)